

GD-CT-AC2105B

2 MP Box HD-TVI Camera WDR



- 2 Megapixel HD-TVI Camera with HD 1080P real time video
- WDR (Wide Dynamic Range) for extreme backlight situations
- Ultra low light camera
- Privacy Zone Masking Function



ESSENTIAL

- Product Line ESSENTIAL: high quality, basic features and remarkably many functions for smaller applications

Item Code: GD-CT-AC2105B

EAN CODE: 4260573063710

Specifications GD-CT-AC2105B

Camera

Image Sensor:	1/3" progressive Scan CMOS
Pixels - Effective:	1920 (H) x 1080 (V)
Sensitivity Colour:	0.005 Lux @ F1.2 (AGC ON)
Shutter Speed:	1/25 (1/30) ~ 1/50,000 s
Slow Shutter:	Support
White Balance:	ATW, Manual

Lens

Lens Mount:	C, CS mount
-------------	-------------

Video

Video Standard:	PAL, NTSC
Col/B&W:	Auto (Electronic) , Colour , B&W
Wide Dynamic Range:	120 dB
Image Enhancement:	BLC, 3D DNR, Mirror,AGC, WDR, Defect Pixel Correction
Frame Rate (Max@Resolution):	PAL: 1080p@25fps NTSC: 1080p@30fps

General

OSD (On Screen Display):	English
Coaxial control:	Control over Coax (CoC)

Pan Tilt Zoom

Number of Privacy Zones:	4 zones, rectangle
--------------------------	--------------------

I/O Interface

Video Outputs:	1x HD-TVI (BNC) , 1x Composite 1.0Vp-p 75 OHM (BNC)
----------------	---

Intelligent Functions

Motion Detection Zones:	4 programmable zones
-------------------------	----------------------

Approvals

Regulation:	CE, EAC, FCC, RoHS Compliant
-------------	------------------------------

Environmental

Operating Temperature:	-30 °C ~ 60 °C (-22 °F ~ 140 °F)
Humidity:	Less than 80%, non condensing

Electrical

Supply Voltage:	12 VDC ±10%
Power Consumption:	Max. 4 W

Mechanical

Dimensions:	70 × 54 × 56 mm (2.73 × 2.13 × 2.2 inch)
Weight:	199 g (0.44 lb)

Item Code: GD-CT-AC2105B

EAN CODE: 4260573063710

Accessories:



GD-AC-VB01



GD-AC-VB02



GD-BR-AWA03



GD-LD-AC2812DC-IR



GD-LD-AC0550DC-IR

Dimensions:

Item Code: GD-CT-AC2105B

EAN CODE: 4260573063710

® Abetechs GmbH (Grundig Security), Düsseldorf, Germany

grundig-security.com

12.08.2022 | Data subject to change without any notice |

Page 3 of 3